

DMX CHANNELS

Mode/Channel	Function	Values	Description
Ch14 Ch16			
1	1	Pan	0-255 PAN Movement
2	2	Pan-fine	0-255 Fine control of Pan movement
3	3	Tilt	0-255 Tilt Movement
4	4	Tilt-fine	0-255 Fine control of Tilt movement
5	5	Color wheel	0-15 Open / white
			16-31 Color 1
			32-47 Color 2
			48-63 Color 3
			64-79 Color 4
			80-95 Color 5
			96-111 Color 6
			112-127 Color 7
			128-189 Forwards rainbow effect from fast to slow
			190-193 Color rotation stop
			194-255 Backwards rainbow effect from slow to fast
6	6	Gobo wheel 1	0-9 Open
			10-19 Gobo 1
			20-29 Gobo 2
			30-39 Gobo 3
			40-49 Gobo 4
			50-59 Gobo 5
			60-69 Gobo 6
			70-89 Gobo 1 shake slow to fast
			90-109 Gobo 2 shake slow to fast
			110-129 Gobo 3 shake slow to fast
			130-149 Gobo 4 shake slow to fast
			150-169 Gobo 5 shake slow to fast
			170-189 Gobo 6 shake slow to fast
			190-255 Rot. gobo wheel cont. rotation slow to fast
7	7	Gobo1 rotation	0-3 No function
			4-127 Forwards gobo rotation from fast to slow
			128-131 Gobo rotation stop
			132-255 Backwards gobo rotation from slow to fast
8	8		No function
9	9	Shutter	0-31 Shutter closed
			32-63 Shutter open
			64-95 Strobe effect slow to fast

DMX CHANNELS

9	9	Shutter	96-127	Shutter open
			128-159	Pulse-effect sequences slow to fast
			160-191	Shutter open
			192-223	Random strobe effect slow to fast
			224-225	Shutter open
10	10	Dimmer	0-255	Dimmer 0%... 100%
11	11	Focus	0-255	In(near)to out(far)
12	12	Prism & Rotation	0-5	OFF
			6-127	ON
			128-255	Rotation from slow to fast
13	13	Speed Pan/Tilt	0-225	Max to min speed
			226-235	Blackout by movement
			236-245	Blackout by all wheel changing
			246-255	No function
14	14	Special function	0-19	No function
			20-29	No function
			30-39	No function
			40-79	No function
			80-84	All motor reset
			85-87	Scan motor reset
			88-90	Colors motor reset
			91-93	Gobo motor reset
			94-96	No function
			99-119	Internal program 1
			120-139	Internal program 2
			140-159	Internal program 3
			160-179	Internal program 4
			180-199	Internal program 5
			200-219	Internal program 6
			220-239	Internal program 7
			240-255	Internal sound program 1
	15	0-255	0-255	Max to min speed
	16	0-255	0-255	Max to min speed